



Christie Lites 120v Socapex Pin-Out

Please note that Christie Lites 120v breakouts use L5-20. Eddison (NEMA 5-15) adapters are available on request.

Christie Lites' 120v Socapex follows industry standard pin-outs.

Socapex Pin Number	Circuit Number
1	Circuit 1 Hot
2	Circuit 1 Neutral
3	Circuit 2 Hot
4	Circuit 2 Neutral
5	Circuit 3 Hot
6	Circuit 3 Neutral
7	Circuit 4 Hot
8	Circuit 4 Neutral
9	Circuit 5 Hot
10	Circuit 5 Neutral
11	Circuit 6 Hot
12	Circuit 6 Neutral
13	Circuit 1 Ground
14	Circuit 2 Ground
15	Circuit 3 Ground
16	Circuit 4 Ground
17	Circuit 5 Ground
18	Circuit 6 Ground
19	Shell

Note: All grounds are bussed together.